



AFP0RE32P | FP0R Expansion units



※Photo may vary from actual product.

Product Number	AFP0RE32P
Part Number	AFP0RE32P
Product	FP0R Expansion unit
Product name	FP0R Expansion units

Spec Detail


As of May 23, 2021

Specifications and design of the products are subject to change without notice for the product improvement.

Item		Specifications
Product Number	AFP0RE32P	
Part Number	AFP0RE32P	
[[Input specifications]]Rated input voltage	24 V DC	
[[Input specifications]]Applied voltage range	21.6 to 26.4 V DC	
[[Input specifications]]Rated input current	4.7 mA approx. (at 24 V DC)	
[[Input specifications]]Input impedance	5.1 kΩ approx.	
[[Input specifications]]Min. ON voltage/ON current	19.2 V / 2 mA	
[[Input specifications]]Max. OFF voltage/OFF current	2.4 V / 1.2 mA	
[[Input specifications]]Response time : OFF→ON	2 ms or less	
[[Input specifications]]Response time : ON→OFF	Same as above	
[[Input specifications]]Insulation method	Photocoupler	
[[Input specifications]]Remark	Since the response time of X0 to X7 is very fast (for high-speed counter input) the FP0 happens to chattering noise as an input signal. To prevent this, it is recommended that the timer should be put in the ladder program.	
[[Output specifications]]Output type	Open collector	
[[Output specifications]]Rated load voltage	24 V DC	
[[Output specifications]]Load voltage allowable range	21.6 to 26.4 V DC	
[[Output specifications]]Max. load current	0.3 A / point (Max. 14 per common terminal)	
[[Output specifications]]OFF state leakage current	1 μA or less	
[[Output specifications]]ON state voltage drop	0.2 V DC or less	
[[Output specifications]]Response time : OFF→ON	1 ms or less	

[[Output specifications]]Response time : ON→OFF	1 ms or less
[[Output specifications]]External power supply : Voltage	21.6 to 26.4 V DC
[[Output specifications]]External power supply : Current	70 mA or less
[[Output specifications]]Surge absorber	Zener diode
[[Output specifications]]Output points per common	16 points / common
[[Output specifications]]Insulation method	Photocoupler


## Accessories




Product Number	<b>AFP0521</b>
Part Number	<b>AFP0521</b>
Product name	<b>I/O cable</b>



Product Number	<b>AFP0523</b>
Part Number	<b>AFP0523</b>
Product name	<b>I/O cable</b>




Product Number	<b>AFP0581</b>
Part Number	<b>AFP0581</b>
Product name	<b>Power cable</b>




Product Number	<b>AFP0803</b>
Part Number	<b>AFP0803</b>
Product name	<b>Mounting plate</b>



Product Number	<b>AFP0804</b>
Part Number	<b>AFP0804</b>
Product name	<b>Mounting plate</b>




Product Number	<b>AFP0807</b>
Part Number	<b>AFP0807</b>
Product name	<b>Wire-press socket</b>




Product Number	<b>AFP0811</b>
Part Number	<b>AFP0811</b>
Product name	<b>Mounting plate</b>



Product Number	<b>AFPX-EFP0</b>
Part Number	<b>AFPX-EFP0</b>
Product	<b>Expansion FP0 Adapter</b>
Product name	<b>Expansion FP0 Adapter</b>




Product Number	<b>DSP2a-DC12V</b>
Part Number	<b>AGP2023</b>
Product name	<b>DSP Relays</b>



Product Number	<b>DSP2a-DC24V</b>
Part Number	<b>AGP2024</b>
Product name	<b>DSP Relays</b>



Product Number	<b>AXY52000FP</b>
Part Number	<b>AXY52000FP</b>
Product	<b>Pressure contact tool</b>
Details	<b>Multi-wire connector pressure contact tool</b>
Product name	<b>Pressure contact tool</b>



Product Number	<b>RT3BB</b>
Part Number	<b>AY30000</b>
Product	<b>4-point Terminal</b>
Details	<b>4-point Terminal, 12, 24V DC</b>
Product name	<b>RT-3 UNIT RELAY 4-POINT TERMINAL</b>






Product Number	<b>RT3SP1-12V</b>
----------------	-------------------



Product Number	<b>RT3SP1-24V</b>
----------------	-------------------



Product Number	<b>RT3SP2-12V</b>
----------------	-------------------

Part Number	AY34001	Part Number	AY34002	Part Number	AY35001
Product	RT-3 Unit relay	Product	RT-3 Unit relay	Product	RT-3 Unit relay
Details	Only for DC use. 12V DC type	Details	Only for DC use. 24V DC type	Details	AC/DC dual use. 12V DC type
Product name	RT-3 UNIT RELAY 4-POINT TERMINAL (PhotoMOS Power type)	Product name	RT-3 UNIT RELAY 4-POINT TERMINAL (PhotoMOS Power type)	Product name	RT-3 UNIT RELAY 4-POINT TERMINAL (PhotoMOS Power type)
					
Product Number	RT3SP2-24V	Product Number	AY3802	Product Number	AY3803
Part Number	AY35002	Part Number	AY3802	Part Number	AY3803
Product	RT-3 Unit relay	Product	Short circuit plate	Product	Short circuit plate
Details	AC/DC dual use. 24V DC type	Details	For RT-3 Unit relay, With insulator	Details	For RT-3 Unit relay, Without insulator
Product name	RT-3 UNIT RELAY 4-POINT TERMINAL (PhotoMOS Power type)	Product name	Short circuit plate	Product name	Short circuit plate

© Panasonic Corporation